

# Product datasheet

Specifications



## APC Smart-UPS On-Line SRT Battery Pack for 8/10kVA Extended runtime model 192V

SRT192BP2

### Overview

Lead time Usually in Stock

### Main

Product or component type	Battery
Battery type	Lead-acid battery
Provided equipment	Documentation CD Installation guide Warranty card
Range of product	Smart-UPS Battery Systems

### Batteries & Runtime

Number of battery free slots	0
Number of battery filled slots	0
Device mounting	Stand alone battery stack
Battery voltage	+/- 192 V
Number of battery replacement quantity	2
Replacement battery	<a href="#">APCRBC140</a>

### Physical

Colour	Black
Height	43.2 cm
Width	13 cm
Depth	68.27 cm
Net weight	91 kg
Mounting mode	Rack-mounted with kit

### Environmental

Ambient air temperature for operation	0...40 °C
Operating altitude	0...10000 ft
Relative humidity	0...95 % non-condensing
Ambient air temperature for storage	-15...45 °C
Storage altitude	0.0000000000...15240.0000000000 m
Storage Relative Humidity	0...95 % non-condensing

## Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	42.000 cm
Package 1 Width	100.000 cm
Package 1 Length	60.000 cm
Package 1 Weight	101.500 kg

## Contractual warranty

Warranty	2 years repair or replace
----------	---------------------------

## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Environmental footprint

Carbon footprint (kg.eq.CO2 per CR, Total Life cycle) 465

Environmental Disclosure [Product Environmental Profile](#)

## Use Better

### Materials and Substances

Packaging made with recycled cardboard Yes

Packaging without single use plastic No

[EU RoHS Directive](#) Pro-active compliance (Product out of EU RoHS legal scope)

SCIP Number 488c31fb-3af8-42cf-9558-1362d000a07e

REACH Regulation [REACH Declaration](#)

## Use Again

### Repack and remanufacture

Circularity Profile [End of Life Information](#)

Removable battery User replaceable

Take-back Yes